

#####

FT-2000

Δf = 20 KHz

BW = 500 Hz

Remarks [Preamp1 2 has 20 sec of latency.](#)

ARRL freq	MDS			in level			IMD			IP3		
	PreAmp.	Amp.OFF	Amp.1	Amp.OFF	Amp.1	Amp.2	Amp.OFF	Amp.1	Amp.2	Amp.OFF	Amp.1	Amp.2
MHz	dBm	dBm	dBm	dBm	dBm	dBm	dB	dB	dB	dBm	dBm	dBm
1,000	-107	-117	-123	-19	-29	-37	89	89	87	26	16	7
1,850	-120	-131	-136	-24	-36	-49	96	95	87	23	11	-6
3,550	-122	-132	-135	-24	-32	-42	98	100	93	24	17	4
7,050	-123	-133	-139	-24	-35	-42	99	98	97	25	14	6
14,200	-122	-132	-139	-31	-42	-49	91	90	90	14	3	-4
21,300	-123	-134	-140	-26	-37	-45	97	97	95	23	12	3
28,500	-122	-132	-136	-31	-43	-50	91	89	86	15	2	-7
50,200	-121	-132	-138	-33	-39	-50	88	93	88	11	8	-6

max
min